

Thank you for purchasing a Sealey product. Manufactured to a high standard this product will, if used according to these instructions and properly maintained, give you years of trouble free performance.



IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. PLEASE KEEP INSTRUCTIONS SAFE FOR FUTURE USE.

1. SAFETY

1.1. GENERAL

- ✓ Ensure the lamp is fully charged before initial use.
- x **DO NOT** turn the lamp on when it is being charged.
- x **DO NOT** shine directly into your, other person's or animal's eyes.
- x **DO NOT** allow children to use the lamp.
- x **DO NOT** handle or move the lamp whilst it is being charged.
- x **DO NOT** use the lamp if you suspect that the battery or the lamp casing is damaged.
- x **DO NOT** leave battery in a discharged state, recharge battery immediately. Before storage, fully recharge the battery, subsequently recharge the battery at least once every six months of non-use.

1.2. ELECTRICAL SAFETY FOR USE OF CHARGER. USE ONLY THE SUPPLIED CHARGER PLUG FOR CONNECTING TORCH TO THE POWER SUPPLY.

- **WARNING!** It is the user's responsibility to read, understand and comply with the following electrical instructions:
 You must ensure the risk of electric shock is minimised by the installation of appropriate safety devices.
 An RCCB (Residual Current Circuit Breaker) should be incorporated in the main distribution board. We also recommend that an RCD (Residual Current Device) is used with all electrical products, particularly portable equipment which is plugged into an electrical supply not protected by an RCCB.

You must also read and understand the following instructions concerning electrical safety.

1.2.1. The Electricity At Work Act 1989

requires all portable electrical appliances, if used on business premises, to be tested by a qualified electrician, using a Portable Appliance Tester (PAT), at least once a year.

1.2.2. The Health & Safety at Work Act 1974 makes owners of electrical appliances responsible for the safe condition of the appliance and the safety of the appliance operator. **If in any doubt about electrical safety, contact a qualified electrician.**

1.2.3. You must ensure that you:

- ✓ Inspect the charger plug, cable and connector for wear and damage to ensure items are safe before connecting to the mains power supply.
 If worn or damaged **DO NOT** use.
- ✓ Important: Check that the voltage marked on the charger plug is the same as the power supply to be used.
- ✓ Uncoil the cable between charger and the lamp.
- x **DO NOT** pull the charger plug from the mains socket by the lead.
- **WARNING! DO NOT use any other type of charger with this product, other than the supplied mains or car charger. Failure to observe this warning could result in injury and or fire and will invalidate the warranty.**
- x **DO NOT** try to take the charger plug apart.

- x **DO NOT** use the charger plug to charge or power any other electrical item.
- x **DO NOT** get the charger wet, or use in wet, damp conditions (for indoor use only).

1.3 Battery Safety

- **WARNING! To reduce the risk of burns or fire:**
- x **DO NOT** Attempt to open, disassemble, modify or service the battery pack.
- x **DO NOT** Crush, puncture, short external contacts or dispose of in fire or water.
- x **DO NOT** Expose to temperatures above 60°C (140°).
- ✓ Replace only with the battery pack designated for this product.
- ✓ Recycle or dispose of used battery as stipulated by local regulation.
- ✓ If the electrolyte in the cells gets on your skin, thoroughly wash with soap and water. If it gets in your eyes, rinse thoroughly with cool water and seek immediate medical attention.

2. INTRODUCTION / SPECIFICATION

Robust inspection lamp with lightweight Lithium-ion battery suitable for the professional user. Incorporates 36 super bright LED's ideal for use in engine bays and under-body inspection. For hands-free applications features both, fold-away 360° swivel hanging hook and an integral magnet.

Battery:	7.4V / 1Ah Li-ion
Charging Time:	4hrs
Operating Time:	5hrs
Operating Temp:	-5°C ~ 45°C
Storage Temp:	-20°C ~ 40°C

3. CHARGING

□ IMPORTANT WARRANTY INFORMATION:

The battery fitted to this lamp is considered to be a consumable item and its ability to accept charge will reduce over time. We will warranty it against mechanical and electrical defect for a period of one year - this does not cover fair wear and tear. If the battery is not properly charged before first use, or regularly conditioned, its capacity will diminish. Under these circumstances we will not replace the battery even if it is less than one year old.

- 3.1 Connect the charger into the charge socket on the lamp. Plug into power supply and turn on, the red charge LEDs on the lamp (Fig.1) will light to show charging has commenced.
- 3.2 When the battery has fully charged (approx 4hrs) the red LEDs will go out and green LED's will come on. Disconnect from mains supply.
- 3.3 During usage, when the battery is low the red charging LED's will start to flash. When this happens switch off the lamp and re-charge.

Note: The Lithium battery does not suffer from memory effect and once fully charged may be stored for up to six months without another charge.

4. OPERATION

- 4.1 Direct the lens away from your eyes before switching on. Switch the lamp 'ON & OFF' using the push switch on the handle.
- 4.2 Suspend the lamp by the hanging hook. When the light is hanging from its hook it can be rotated through 360° for more precise positioning.
- 4.3 You may also use the integral magnet to attach the lamp to metalwork such as under-bonnet.

Note: LED arrays are designed to allow individual LEDs to cease functioning without causing the entire array to fail. This could be as a result of shock or impact. Shock or impact will invalidate warranty.

Environmental Protection



Recycle unwanted materials instead of disposing of them as waste. All tools, accessories and packaging should be sorted, taken to a recycle centre and disposed of in a manner which is compatible with the environment.



When the product is no longer required, it must be disposed of in an environmentally protective way.



Battery Removal

1. Remove six screws and open casing from front.
2. Clip wires attached to main board and dispose of battery according to local authority guidelines.

Under the Waste Batteries and Accumulators Regulations 2009, Jack Sealey Ltd are required to inform potential purchasers of products containing batteries (as defined within these regulations), that they are registered with Valpak's registered compliance scheme. Jack Sealey Ltd's Batteries Producer Registration Number (BPRN) is BPRN00705



Parts support is available for this product. To obtain parts please email sales@sealey.co.uk or phone 01284 757500.

NOTE: It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice.

IMPORTANT: No liability is accepted for incorrect use of this product.

WARRANTY: Guarantee is 12 months from purchase date, proof of which will be required for any claim.

INFORMATION: For a copy of our latest catalogue and promotions call us on 01284 757525 and leave your full name and address, including postcode.



Sole UK Distributor, Sealey Group,
Kempson Way, Suffolk Business Park,
Bury St. Edmunds, Suffolk,
IP32 7AR

01284 757500

01284 703534



www.sealey.co.uk



sales@sealey.co.uk