

Thank you for purchasing a Sealey product. Manufactured to a high standard this product will, if used according to these instructions and properly maintained, give you years of trouble free performance.



IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. PLEASE KEEP INSTRUCTIONS SAFE FOR FUTURE USE.

1. SAFETY

1.1. GENERAL

- x **DO NOT** shine directly into your, other person's or animal's eyes.
- x **DO NOT** allow children to use the inspection lamp.
- x **DO NOT** handle or move the inspection lamp whilst it is being charged.
- x **DO NOT** use the inspection lamp if you suspect that the battery or the inspection lamp casing is damaged.
- x **DO NOT** leave battery in a discharged state: recharge battery immediately.
If the inspection lamp is not in use, recharge the battery at least every 3 months.

1.2. ELECTRICAL SAFETY FOR USE OF CHARGER.

USE ONLY THE SUPPLIED CHARGER PLUG FOR CONNECTING INSPECTION LAMP TO THE POWER SUPPLY.

WARNING! It is the user's responsibility to read, understand and comply with the following electrical instructions:

You must ensure the risk of electric shock is minimised by the installation of appropriate safety devices. An RCCB (Residual Current Circuit Breaker) should be incorporated in the main distribution board. We also recommend that an RCD (Residual Current Device) is used with all electrical products, particularly portable equipment which is plugged into an electrical supply not protected by an RCCB.

You must also read and understand the instructions concerning electrical safety paragraph 1.2.1 onwards.

1.2.1. The Electricity At Work Act 1989 requires all portable electrical appliances, if used on business premises, to be tested by a qualified electrician, using a Portable Appliance Tester (PAT), at least once a year.

1.2.2. The Health & Safety at Work Act 1974:

Makes owners of electrical appliances responsible for the safe condition of the appliance and the safety of the appliance operator. If in any doubt about electrical safety, contact a qualified electrician.

1.2.3. You must ensure that you:

- ✓ Inspect the charger plug, cable and connector for wear and damage to ensure items are safe before connecting to the mains power supply. If worn or damaged **DO NOT** use.
- ✓ Important: Check that the voltage marked on the charger plug is the same as the power supply to be used.
- ✓ Uncoil the cable between charger and the inspection lamp.
- x **DO NOT** pull the charger plug from the mains socket by the lead.
- x **DO NOT** use any other type of charger with this inspection lamp.
- x **DO NOT** try to take the charger plug apart.
- x **DO NOT** use the charger plug to charge or power any other electrical item.
- x **DO NOT** get the charger wet, or use in wet, damp conditions (for indoor use only).
- WARNING! NEVER** substitute a standard 13amp 3 pin plug, or any other type of plug, for the charger plug.

IMPORTANT: LED arrays are designed to allow individual LED's to cease functioning without causing the entire array to fail. This could be as a result of shock or impact.
Shock or impact will invalidate the warranty.

2. INTRODUCTION

- Impact-resistant, waterproof housing.
- 30 LED's to produce pure white light.
- 360° swivel hanging hook.
- Ideal for use in engine bays and dull work areas.

- Battery service life: Up to 8 hours per charge.
- Charging time: 6 hours.
- Battery type: NiMH 4.8V 2.4Ah.
- Charger output: 8V/600mA.

3. CHARGING

IMPORTANT: Fully charge the lamp before first use, charge for 6 hours.

DO NOT let the lamp completely discharge.

- 3.1 When the red LED lights on the lamp during use, it indicates that charging is required.
- 3.2 Make sure the inspection lamp is switched off before commencing charging.
- 3.3 Uncoil the charging lead and plug the connector into the charging socket at the base of the inspection lamp.
- 3.4 Plug the power lead from the charger into the mains supply.

- 3.5 When charging a red LED will illuminate on the lamp, when the red LED turns green the lamp is fully charged and ready for use.
- 3.6 Unplug the charger from the mains supply. Unplug the charging lead from the inspection lamp.
- 3.7 The inspection lamp will operate continuously for up to 8 hours on one charge.
- 3.8 Charger Part No: **LED30.V2.C**

NOTE! If lamp is not used, recharge the battery at least every 3 months.

4. OPERATION

- 4.1 **DIRECT THE LENS AWAY FROM YOUR EYES BEFORE SWITCHING ON.** Switch the inspection lamp ON & OFF using the red push button switch on top of the casing.
- 4.2 To suspend the inspection lamp, use the hanging hook at the top of the case. When the inspection lamp is hanging from its hook, it can be rotated through 360° for more precise positioning.

NOTE: It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice.

IMPORTANT: No liability is accepted for incorrect use of this product.

WARRANTY: Guarantee is 12 months from purchase date, proof of which will be required for any claim.

INFORMATION: For a copy of our latest catalogue and promotions call us on 01284 757525 and leave your full name and address, including postcode.

