



INSTRUCTIONS FOR:

LED WORK SPOTLIGHT 12W/48W

MODEL NO: **WL12W, WL48W**

Thank you for purchasing a Sealey product. Manufactured to a high standard, this product will, if used according to these instructions, and properly maintained, give you years of trouble free performance.



IMPORTANT: PLEASE READ THESE INSTRUCTIONS CAREFULLY. NOTE THE SAFE OPERATIONAL REQUIREMENTS, WARNINGS & CAUTIONS. USE THE PRODUCT CORRECTLY AND WITH CARE FOR THE PURPOSE FOR WHICH IT IS INTENDED. FAILURE TO DO SO MAY CAUSE DAMAGE AND/OR PERSONAL INJURY AND WILL INVALIDATE THE WARRANTY. KEEP THESE INSTRUCTIONS SAFE FOR FUTURE USE.

1. SAFETY

1.1. ELECTRICAL SAFETY

- WARNING!** It is the responsibility of the owner and the operator to read, understand and comply with the following: You must check all electrical products, before use, to ensure that they are safe. You must inspect power cables, plugs, sockets and any other connectors for wear or damage.
 - 1.1.1. Ensure that cables are always protected against short circuit and overload.
 - 1.1.2. Regularly inspect power supply cables check all connections to ensure that none are loose.
 - 1.1.3. **Important:** Ensure that the voltage marked on the appliance matches the power supply to be used and that the circuit is fitted with the correct fuse. If in doubt, consult a qualified technician to connect the spotlight to a fused and switched DC supply.
 - 1.1.4. **DO NOT** pull or carry the spotlight by the power cable.
 - 1.1.5. **DO NOT** use worn or damaged cables, plugs or connectors. Immediately have any faulty item repaired or replaced by a qualified technician.

2. INTRODUCTION

Model No: WL12W

Spotlight with 4 x 3W Epistar™ high power LEDs producing up to 840 lumens output. IP67 Rated with a powder coated die cast aluminium housing. Suitable replacement for traditional halogen work lights with up to 80% less power consumption. Supplied with grade 304 stainless steel mounting bracket and fixings.

Model No: WL48W

Spotlight with 16 x 3W Epistar™ high power LEDs producing up to 3450 lumens output. IP67 Rated with a powder coated die cast aluminium housing. Suitable replacement for traditional halogen work lights with up to 12% less power consumption. Supplied with grade 304 stainless steel mounting bracket and fixings.

3. SPECIFICATION

Model No: **WL12W**
Power:..... 12W
Lumen Output:..... 840lm
Supply:..... 9-32V DC
Dimension: Ø80mm

Model No: **WL48W**
Power:..... 48W
Lumen Output:..... 3450lm
Supply:..... 9-32V DC
Dimensions: 125 x 110mm



Environmental Protection



Recycle unwanted materials instead of disposing of them as waste. All tools, accessories and packaging should be sorted, taken to a recycling centre and disposed of in a manner which is compatible with the environment. When the product becomes completely unserviceable and requires disposal, drain off any fluids (if applicable) into approved containers and dispose of the product and the fluids according to local regulations.



WEEE Regulations

Dispose of this product at the end of its working life in compliance with the EU Directive on Waste Electrical and Electronic Equipment (WEEE). When the product is no longer required, it must be disposed of in an environmentally protective way. Contact your local solid waste authority for recycling information.

NOTE: It is our policy to continually improve products and as such we reserve the right to alter data, specifications and component parts without prior notice.

IMPORTANT: No liability is accepted for incorrect use of this product.

WARRANTY: Guarantee is 12 months from purchase date, proof of which will be required for any claim.

INFORMATION: For a copy of our latest catalogue and promotions call us on 01284 757525 and leave your full name and address, including postcode.



Sole UK Distributor, Sealey Group,
 Kempson Way, Suffolk Business Park,
 Bury St. Edmunds, Suffolk,
 IP32 7AR

01284 757500

01284 703534

www.sealey.co.uk

sales@sealey.co.uk